

Fronius Wifi reconnection guide.

Please watch our YouTube video for more information regarding this topic:

https://youtu.be/TUGA-2l_wwA?t=249

Steps:

1. On the inverter, go to **Setup** → **Wifi Access Point** → **Activate**.
 2. On your phone, tablet, or laptop, go to **WiFi settings** and connect to the **Fronius_240.xxxxxx** network using the password **12345678**.
 3. Open a web browser and type in **192.168.250.181**.
 4. If the page that loads is “**Current Overview**” (showing real-time production), please skip to the next solution.
 5. If the page that loads is “**Network Setup**”, click on “**Skip Network Commissioning**” at the bottom of the page.
 - If the page shows “**Network Status**”, click “**Continue via Access Point**” at the bottom.
 6. Create the **Admin password** (e.g. admin123), then click forward to complete the wizard.
-

Restart the Wizard (if Date and Time are incorrect)

Please follow the steps below to correct the date and time automatically by resetting the wizard:

Steps:

1. On the inverter, go to **Setup** → **Wifi Access Point** → **Activate**.
 2. On your phone, tablet, or laptop, go to **WiFi settings** and connect to the **Fronius_240.xxxxxx** network using the password **12345678**.
 3. Open a web browser and type in **192.168.250.181**, then press Enter to load the web interface.
 4. On the web interface, click on “**Start assistant**” (right-hand side), then click on **Solar.web wizard**.
 5. The **General** page will appear (information should already be filled in), click forward. Then under **Inverter**, click forward again.
 6. The next page will be **Network Setup**. Click on “**Skip Network Commissioning**” (bottom right-hand side).
 7. Create the **Admin password** (e.g. admin123), then click forward to complete the wizard.
-

Ensure Archive Data is Activated

Repeat **Steps 1–3** from above, then follow the steps below:

Steps:

4. On the web interface, click on **Settings** (right-hand side).
 5. On the left-hand menu, select **Fronius Solar.web**.
 6. At the bottom of the page, check that “**Send Archive Data to Fronius Solar.web**” is set to **hourly**.
 7. If not, change it and click the **tick at the top of the page** to save the changes.
-

Restart the Datalogger (if update is stuck)

If the Datamanager card update is stuck on “**Starting update, Please wait**”, restart the Datalogger and try again.

Repeat **Steps 1–3** from above, then follow the steps below:

Steps:

4. Click on **System Information** (right-hand side).
5. Scroll down and click on the **Datalogger Restart** button (bottom left).
6. Accept the pop-up message. The Datamanager will then restart.