



FRONIUS WIFI RECONNECT GUIDE

1. Go to Your Fronius Inverter Screen
2. Press the RETURN button (third button from the Left) to go back to Main Menu
3. Press ACROSS until you find setup than hit ENTER (very right button)
4. SELECT Wifi Access Point, than select ACTIVATE
5. Once Activated, go to your Smartphone or devices Wifi Settings
6. Select the network Fronius_240XXXX, and CONNECT. Password is 12345678
7. Once connected, open your preferred Web Browser (Safari, Google Chrome, Internet Explorer)
8. Type in the address bar 192.168.250.181 and press ENTER or SEARCH
9. Wait for the page to load, select SETTINGS on the right side of the page.
10. Once in settings, locate NETWORK on the left side of the page.
11. Select WLAN if using Wifi, LAN if using Ethernet Cable
12. Find your Wifi Network you wish to connect to, Select it and press SET
13. Type in your Wifi Password and press SAVE
14. Press the TICK located on the top right of the page. (If you do not press the tick the settings will not be entered).
15. Go to your devices Wifi Settings, CONNECT back to your Wifi Network
16. Proceed To solarweb.com or your solarweb App, The inverter will now be back online.

